



MAGIC 9000 TERMINALS TRAVELLING AND/OR STORAGE

MagIC 9000 terminals must be placed in "SLEEP MODE"
(see below) when travelling and/or storing.

- ✍ Make sure the handset wire (if you have one) is removed from the base.
- ✍ Press the FCN key
- ✍ Press the arrow key directly under the ADM symbol.
- ✍ Press the down arrow key until the cursor is on the words "POWER OFF"
- ✍ Press the OK key
- ✍ The terminal will shut off and now is ready removal of the large gray battery from the back of the unit (Never Remove the smaller Lithium Battery).
- ✍ The terminal is now ready for storage and/or shipping

To Re-activate MagIC 9000 Units from Sleep Mode

- ✍ Plug-in your MagIC 9000 charger base to the electrical supply.
- ✍ Replace the large gray battery into the back of the unit. Place the handset into the base/cradle after it has been plugged in.
- ✍ The terminal should be active and the spinning globe should now be visible.

Note: If the spinning globe is not visible, please repeat the above procedure.